



**\*Technical Bulletin\***

(1005685 Rev. B)

February 6, 2007

**Models Affected:**

1005249 (4K2X2HSP4GB-SBLN)

1005515 (SV-4001-X2)

**Model Serial Numbers:**

145161-145176, 145248-145265, 145439-145442, 145491-145494, 145504-145509, 145511, 145527-145531

**Details:**

This bulletin shows the steps required to rotate the 2 power receptacles on the rear of SBLN 4U servers.

**Tools required:**

- 1) 1/4 Inch Nut Driver

**Directions**

- 1) Obtain access to rear of system as shown in Figure 1.
- 2) Remove power cord retention wires.
- 3) Remove the receptacle mounting screws using the 1/4-Inch Nut Driver.



Figure 1

- 4) Pull power receptacles out approximately 2 inches. Rotate the power receptacles and insert back into unit.



- 5) Using the previously removed screws and the ¼-Inch Nut Driver, fasten the power receptacles to the server. Line up the hole going through the screw heads to be as horizontal as possible.
- 6) Replace power cord retention wires.

